

(19)



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11)

EP 1 069 798 A1

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:
17.01.2001 Bulletin 2001/03

(51) Int Cl.7: **H04Q 7/38**, H04L 1/00,
H04L 1/08

(21) Application number: **99305516.9**

(22) Date of filing: **12.07.1999**

(84) Designated Contracting States:
**AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE**
Designated Extension States:
AL LT LV MK RO SI

(72) Inventors:
• **Freiberg, Lorenz Fred**
Swindon, Wiltshire SN5 6HG (GB)
• **Mueckenheim, Jens**
90411 Nuremberg (DE)


(71) Applicant: **LUCENT TECHNOLOGIES INC.**
Murray Hill, New Jersey 07974-0636 (US)

(74) Representative: **Williams, David John et al**
Lucent Technologies UK Limited,
5 Mornington Road
Woodford Green, Essex IG8 0TU (GB)

(54) **Universal mobile telephone system network with improved rate matching method**

(57) In a UMTS network in which a single user can transmit or receive a number of services having different transmission power requirements over a single channel, a method of determining for each service the number of bits to be punctured or repeated to provide rate matching by the steps of deriving for each service the Energy per Bit per Noise density E_b/N_0 required to achieve a desired Bit Error Rate; from each E_b/N_0 deriving a value of the Energy per coded Symbol per Noise density E_s/N_0 ; and from E_s/N_0 deriving a rate matching factor by

which that E_s/N_0 can be matched to the minimum Energy per coded Symbol per Noise density applicable to the channel in which the services are multiplexed. The values of E_b/N_0 are stored in a look up table in the BTS and each mobile; the BSC generates values of semi static rate matching factors and spreading factors for each service and transmits them to the BTS and mobiles so that the mobile can calculate from the received values and the values stored in the look up table the number of bits to be punctured or repeated.



EP 1 069 798 A1

Description

[0001] This invention relates to a Universal Mobile Telephone System (UMTS) network and more especially to a method of calculating the number of bits to be punctured or repeated to achieve effective rate matching.

[0002] In a UMTS system, the technique of time multiplexing is used to combine different services required by one user. The services have different Quality of Service (QoS) requirements, such as signal power with respect to noise and interference power, and latency restrictions which lead to different requirements of transmission power; transmission power must therefore be adjusted so that in any one transmission channel the QoS is maintained for the service making the highest demand, but simultaneously transmission power is minimised.

[0003] To achieve this, and also to adapt the symbol data rate to the physical channel data rate, the method of rate matching is used, ie, some bits are punctured or repeated. The principle of rate matching is described by the Ericsson company in the paper "Description of Rate Matching in UTRA/FDD," TDoc SMG2 UMTS L1 235/98 and by the Nokia company in the paper "Mapping Rule for semi static rate matching," TDoc SMG2 UMTS L1 476/98. The publication by Nokia also proposes a method of deriving the number of bits to be punctured or repeated to achieve the required QoS for two different services by interpolation methods. However, interpolation cannot be applied to more than two services, which is a substantial limitation on the network and also the algorithm is complex.

[0004] According to the invention, in a UMTS network in which a plurality of services of a single user having different transmission power requirements are multiplexed in one channel and the technique of rate matching is applied, a method of determining for each service the number of bits to be punctured or repeated characterised by the steps of

deriving for each service the Energy per Bit per Noise density E_B/N_0 required to achieve a desired Bit Error Rate;

from each E_B/N_0 deriving a value of the Energy per coded Symbol per Noise density E_S/N_0 ;

and from E_S/N_0 deriving a rate matching factor by which that E_S/N_0 can be matched to the minimum Energy per coded Symbol per Noise density applicable to said one channel.

[0005] The invention will now be described by way of example only with reference to the accompanying drawings in which:-

Figure 1 is a schematic view of a UMTS network at network level;

Figure 2 shows the conventional steps in UMTS transport channel multiplexing for the uplink;

Figure 3 shows rate matching gain;

Figure 4 shows the major steps in a first example of a method according to the invention; and

Figure 5 shows a relationship between channel coding and rate matching in a second example of a method according to the invention.

[0006] In Figure 1, a UMTS network 10 comprises a number of mobile users 12, 14 each connectable to a base station BTS/Node B 16. The BTS 16 is connected through a Base Station Controller BSC 18 in a Radio Network Controller (RNC) 20 to a Mobile Switching Controller (MSC) 21 in the UMTS Core Network (CN) 22. The CN 22 provides connections to the public switched telephone network PSTN 24, integrated services digital network ISDN 26 and the internet 28.

[0007] The Radio Access Network (RAN) comprises the mobile users 12, 14 and the BTS 16. To multiplex signals in the RAN in the uplink direction (from the mobile 12, 14 to the BTS 16), the arrangement of Figure 2 is used; the steps are performed in the appropriate mobile 12 or 14. Figure 2 shows transport channel multiplexing for the uplink and is taken from the standard TS 25.212 V1.1.0 (1999-06).

[0008] In Figure 2, the steps to encode services with identical QoS requirements are shown within box 30, and identical steps to encode a set of different services are performed within box 31 (steps not shown). The steps comprise Cyclic Redundancy Coding (CRC) steps 40 for identical services, (but in this invention a single service at step 40 is considered), a first multiplexing step 41, channel coding step 42, first interleaving step 43, radio frame segmentation step 44 and rate matching step 45.

[0009] The equivalent rate matching step 55 is shown in box 31.

[0010] The outputs of the two boxes 30, 31 are combined in a second multiplexing step 60 followed by a physical channel segmentation step 61, second interleaving step 62, and physical channel mapping step 63; the outputs are

then provided to respective Dedicated Physical Data Channels DPDCH 64.

[0011] The reverse steps are performed for uplink de-multiplexing at the BTS 16.

[0012] This entire procedure exists also in the downlink direction, ie from the BTS 16 to a mobile 12 or 14.

[0013] While the rate matching steps 45, 55 are indicated as separate, they are in fact interrelated because rate matching is based on the relative QoS requirements of different sets of services, and because the channel must be able to support the combined rate matching output of all services, and this interrelationship is indicated at 56 but, as stated above, the interrelationship has previously been specified only for rate matching of two services by interpolation.

[0014] By application of the method of the invention, rate matching of more than two different services is achievable.

[0015] In the rate matching steps 45, 55, a set of puncturing or repetition factors is determined based on the requirements that:-

a) desired transmission quality requirements of each transport channel is fulfilled and not significantly exceeded. This means that required transmission power to meet quality requirements for all transport channels is as low as possible.

b) on the uplink, the total bit rate after transport channel multiplexing is identical to the total channel bit rate of the dedicated physical channels allocated.

c) on uplink and downlink, the total allocated code resource should be minimised.

d) the puncturing factors should not exceed a certain maximum puncturing factor, specific for each transport channel.

[0016] In the current UMTS concept there are two types of rate matching specified:

(i) Semi-static Rate Matching: this is used to balance the transmission power requirements of different services, which are multiplexed to one Common Composite Traffic Channel (CCTrCH). This function is also known as 'ES/NO-balancing' - balancing the ratio of symbol energy to noise density. Because the elements related to service multiplexing are decided by the Radio Resource Control (RRC) layer, this physical layer function is controlled by RRC via the semi-static part of TFCI.

(ii) Dynamic Rate Matching: this is used in the uplink to adapt the symbol data rate to the data rate of the CCTrCH in order to preserve continuous transmission. It is an autonomous function of the physical layer. Dynamic rate matching is performed through discontinuous transmission (DTX) in the downlink.

[0017] In a single channel, several services (as indicated by boxes 30, 31) must be multiplexed which have different bit rates and different types of coding. For example a low rate video using 144 kbps and turbo coding; a voice service at 13kbps using convolutional coding, plus signalling information, also using convolutional coding.

[0018] Each service will have a QoS requirement, and an important part of that requirement is the Energy per Bit per Noise Density E_b/N_0 required to achieve the desired Bit Error Rate BER. The E_b/N_0 for a service will apply only to specific measurement conditions, such as the environment (pedestrian, indoor, vehicular etc). the level and type of coding (turbo, conventional), the level of physical layer control signalling (Dedicated Physical Control Channel DPCCCH overhead) and the spreading factor. Conventionally, the requirements have been calculated by simulation or by measurement of a service in a particular environment.

[0019] When services having different E_b/N_0 requirements are to be multiplexed, certain differences can be adjusted by comparing E_b/N_0 requirements; eg, the DPCCCH consists of pilot symbols, power control and Transport Format Combination Indicator (TFCI) symbols only, with the amount of energy required being relatively independent of the service and dependent only on environment. Also, most UMTS services use rate 1/3 coding schemes with similar levels of extra overhead such as tail bits. Adjustment of power is therefore relatively easy.

[0020] Other differences cannot be derived from E_b/N_0 values. For example, when services are multiplexed, the Coded Composite Transport Channel CCTrCH will use a spreading factor which is different to the spreading factor that each service would use individually, and variations may be wide. A voice service normally uses a spreading factor of 128 and could be mapped onto a CCTrCH using a spreading factor of 4, when sent together with other services.

[0021] The method of the invention solves this problem.

[0022] In the invention, a look up table of E_b/N_0 is created; E_b/N_0 is expressed as Energy per coded Signal versus noise density, ie E_s/N_0 . It must be understood that E_b/N_0 is not the bit energy when the data is uncoded, but is the equivalent energy per bit assuming a certain coding scheme, spreading factor and environment. Therefore for every value of E_b/N_0 there is a unique value E_s/N_0 which in this context does not include the DPCCCH overhead.

[0023] Using the E_s/N_0 value for each service i , $(E_s/N_0)_i$, a required level of semi-static rate matching can be calculated. Since it is impossible for the E_s/N_0 for the CCTrCH to satisfy the $(E_s/N_0)_i$, rate matching is needed, such that each service achieves its desired $(E_s/N_0)_i$.

[0024] The E_s/N_0 for the CCTrCH is set as E'_s/N_0 , which is likely to equal the E_s/N_0 for one of the constituent services; all other services are therefore forced to use semi-static rate matching. In some circumstances however the E'_s/N_0 does not equal the E_s/N_0 for a constituent service, in which case all services will be required to use rate matching. The relationship between $(E_s/N_0)_i$ and E'_s/N_0 is given by

$$\frac{E'_s}{N_0} \cdot N_{R,i} = G(SRF_i) \cdot \left(\frac{E_s}{N_0} \right)_i \cdot N_{S,i} \quad (1)$$

In order to be satisfied with E'_s/N_0 , the service must use a semi static rate matching factor, SRF_i , of

$$SRF_i = \frac{N_{R,i}}{N_{S,i} \cdot G(SRF_i)}$$

where

$N_{R,i}$ is the number of coded symbols after semi static rate matching
 $N_{S,i}$ is the number of code symbols before rate matching,

and $G(SRF_i)$, illustrated in Figure 3, is the coding gain associated with the level of semi-static rate matching.

[0025] Thus any service i must use a semi-static matching factor SRF_i .

[0026] Generally, it can be assumed that adjusting the energy by adding extra symbols is equivalent to adjusting the E_s/N_0 . Therefore if SRF_i is limited to greater than -1 dB, $G(SRF_i)$ is 1 (0dB). However, puncturing alters the coding scheme used, which results in a loss greater than the decrease in energy. Moreover, repetition may result in extra time diversity, thereby providing coding gain beyond the increase in energy. Repeating some of the bits in a transport block may not be equivalent to increasing the energy of *all* of the bits. Finally, the gain achieved by repetition depends on the combining method implemented.

[0027] An additional requirements is that the semi-static rate matched transport block (on leaving box 30 or box 31 in Figure 2) must fit into a physical channel having bits per frame N_{Frame} . One time frame is 10 milliseconds, and contains N_S symbol bits where

$$N_S = 16 \cdot \sum_{j=1}^m N_{dataj}$$

where $m=1$ for single code transmission, and m is greater than 1 for multicode transition, ie where more than one DPDCH is assigned to one CCTrCH, as in the method according to the invention.

[0028] In the uplink the number of data bits N_{data} of one DPDCH in a time slot (0.625 ms) is simply given by $N_{data} = 10 \cdot 2^k$, $k = 0 \dots 6$. In the downlink, due to time multiplex of DPDCH and DPCCH it is given by $N_{data} = 20 \cdot 2^k \cdot N_{pilot} \cdot N_{TPC} \cdot N_{TFC}$, $k = 0 \dots 6$. The spreading factor of the related DPCH in uplink and downlink is $SF = 256/2^k$, thus it may range from 256 down to 4. The rate matching factor RF_i is given by the product of the dynamic rate matching factor DRF and the semi static rate matching factor SRF_i by $RF_i = DRF \cdot SRF_i$. The dynamic rate matching factor DRF is equal for all multiplexed services, but the semi static rate matching factor SRF_i depends on the service. Two basic conditions must be fulfilled by the rate matching principle:

$$\frac{E'_s}{N_0} = \left(\frac{E_s}{N_0} \right)_i \cdot \frac{1}{RF_i} \quad (2)$$

$$\sum_{i=1}^n N_{Ri} = \sum_{i=1}^n N_{Si} \cdot RF_i = DRF \cdot \sum_{i=1}^n N_{Si} \cdot SFR_i = N_{Total} \quad (3)$$

where E_s^*/N_0 is the E_s/N_0 set point for the CCTrCH. (Through dynamic rate matching each service will achieve its individual target of $(E_s/N_0)_i$) n is the number of services multiplexed onto the CCTrCH.

In the downlink, DRF is set to 1. Discontinuous transmission (DTX) is used instead of dynamic rate matching. DTX means that when $N_{frame} > N_{total}$, the difference in the number of bits is simply not transmitted. Hence N_{total} is simply the sum of all N_{Ri} , as defined for semi-static rate matching. Therefore, generally $E_s^*/N_0 = E_s/N_0$ in the downlink. However, if N_{total} is just slightly larger than N_{frame} it is possible to set DRF to between 0.8 and 1.0, thereby applying puncturing instead of DTX to adjust the CCTrCH rate. This method avoids using the next lower spreading factor and the resulting high level of repetition.

In the uplink, N_{frame} must be equal to N_{total} , since DTX cannot be used. Therefore, DRF is defined by equations 2 and 3, as well as:

$$N_{frame} = N_{total}$$

[0029] Figure 4 indicates five major steps of the method according to the invention; as indicated, steps 1, 2 and 3 are performed in the BSC (reference 18 in Figure 2) while steps 4 and 5 are performed in the BTS 16 and mobiles 12, 14.

Step 1: In step 1, Inputs to the rate matching algorithm are the values $(E_s/N_0)_i$ which are determined for each specific service and the number of data bits which is explicitly given by the data rate N_{Si} .

Step 2: During this step the rate matching factors, SFR_i and DRF_i are calculated (equations 1 and 3). First an initial spreading factor (SF) estimate is chosen based such that

$$N_{frame} > \sum_{i=1}^n N_{Si}$$

Using this initial estimate for SF, the set of $(E_s/N_0)_i$ are identified from the look up table for the relevant environment and level of coding. N_{total} is calculated. If $N_{frame} < 0.8 \cdot N_{total}$, the value of SF is too large and Step 2 is performed again using the new value for the spreading factor of $SF_{new} = SF/2$.

Step 3: The outputs from the RRC part of algorithm are the semi static rate matching factors for each DCH, which are element of the semi-static part of TFCI and the spreading factors for each service combination, which may be part of the dynamic part of the TFCI. The TFCI is used to inform the physical layer of both, the mobiles 12, 14 and the NodeB 16, what physical transmission parameter has to be chosen.

Step 4: This is the first step of the execution part of the rate matching algorithm. Only the TFCI is necessary to derive all other parameters for rate matching. The dynamic rate matching factor is automatically given by knowing the semi static rate matching factor for a certain service combination. An example is given in the paper by Mitsubishi Electric and Siemens: "Determination of Rate Matching Parameters for Service Multiplexing," Tdoc 3GPP TSG-RAN WG1 710/99. Now the rate matching factor for each service is calculated by $RF_i = DRF \cdot SFR_i$. From this, the number of punctured / repeated bits is simply $N_{Rmi} = (RF_i - 1) \cdot N_{codi}$.

Step 5: The last step performs puncturing / repetition of the bits using the value of N_{Rmi} . Several techniques can be applied and an example is given in the paper by Philips "Service Multiplexing," TDoc SMG2 UMTS L1 229/98.

[0030] Advantages of the method according to the invention are that the final calculation of the number of bits to be repeated or punctured, and the puncturing or repetition themselves, are carried out in the physical layer in an autonomous arrangement; that the semi-static rate matching is explicitly given; and that the method derives a spreading factor for each service combination for use by the dynamic part of the TFCI. The last two advantages are in contrast to the proposal by the Nokia company (reference above) in which the TFCI elements are not explicitly given but must be calculated separately from the number of bits.

[0031] Overall, the method of the invention leads to a significant decrease in transmitted power and hence an im-

provement in overall system capacity.

Example

5 **[0032]** In the following example, three services are multiplexed for a user in a vehicle. In the downlink a spreading factor of 4 is selected resulting in CCTrCH rate of 512ksps. The services are as follows:-

144 kbps low rate video, using turbo coding, requiring $E_s/N_O = 5$ dB.

13 kbps voice, using convolutional coding, requiring $E_s/N_O = 8$ dB.

10 Signalling information, using convolutional coding, requiring $E_s/N_O = 9$ dB.

$E'_s/N_O = 5$ dB, hence rate matching is required by each service to achieve the desired $(E_s/N_O)_i$ is:

video: 0dB

voice: 3 dB

signalling: 4 dB.

15

[0033] This is shown in table 1, under the rate matching row. There is no Dynamic rate matching, Discontinuous transmission is used to match T_{frame} and T_{total} .

20

25

30

35

40

45

50

55

Table 1. Multiplexing example: Downlink.

Component Services	Voice, Low Video + Signalling		
	Voice	Low Video	Signalling
Transport Block size	320	320	80
Transmission interval and first interleaver duration (ms)	20	10	10
Number of Transport Blocks / frame	1	5	1
Number of Bits/transmission interval	320	1600	80
Add CRC	336	1680	96
Coding Interval (ms)	20	10	10
Number of bits / coding interval	336	1680	96
Add Tail bits / Trellis Termination	344	1692	104
Convolutional Encoding	1032		312
Turbo Encoding		5076	
Rate Match factor, dB (-20% = -1dB)	3.01	0.00	3.98
Rate Matching / Trans. Interval	1032	0	468
Add DTX indication / Trans. Interval	2096	12	1780
First interleaver size	4160	5088	2560
Interleaver check mod(1st IL / 32)	0	0	0
second interleaver duration (ms)	10		
second interleaver size	9728		
number of physical channels	1		
Pilot bits / slot	16		
TFCH bits per slot	8		
TPC bits / slot	8		
Total DPCCH field / frame	512		
Total bits / physical channel frame	10240		
Physical Channel rate (ksps)	512		

[0034] In the uplink a spreading factor of 4 was chosen resulting in a CCTrCH rate of 1024 ksps. The services are defined by:

144 kbps low rate video, using turbo coding, requiring $E_s/N_0 = 4$ dB.

13 kbps voice, using convolutional coding, requiring $E_s/N_0 = 7$ dB.

Signalling information, using convolutional coding, requiring $E_s/N_0 = 8$ dB.

If $E_s/N_0 = 4$ dB, then the rate matching is required by each service to achieve the desired $(E_s/N_0)_i$ is:
video: 0 dB voice: 3 dB signalling: 4 dB.

This is shown in table 2, under the rate matching row. Additionally, dynamic rate matching is used to match T_{frame} and T_{total} resulting is a further gain due to repetition of 1.7 dB. Hence $E_s^*/N_0 = E_s/N_0 - 1.7 = 2.3$ dB.

The number will vary slightly in tables 1 and 2 in order to achieve number of bits that agree with realistic interleaver size; interleaver sizes must be divisible by the number of slots.

Table 2. Multiplexing example: Uplink.

Combined Service	Voice, Low Video + Signalling		
Component Services	Voice	Low Video	Signalling
Transport Block size	320	320	80
Transmission interval and first interleaver duration (ms)	20	10	10
Number of Transport Blocks / frame	1	5	1
Number of Bits/transmission interval	320	1600	80
Add CRC	336	1680	96
Coding Interval (ms)	20	10	10
Number of bits / coding interval	336	1680	96
Add Tail bits / Trellis Termination	344	1692	104
Convolutional Encoding	1032		312
Turbo Encoding		5076	
Padding	24	12	8
First interleaver size	1056	5088	320
IL check: mod(1 st IL per frame / 16)	0	0	0
Rate Match factor, dB (-20% = -1dB)	4.75	1.69	5.76
Rate Matching / Trans. Interval	2052	2414	864
segmentation check: mod(Tx.Int./frame)	0	0	0
second interleaver duration (ms)	10		
second interleaver size	10240		
number of physical channels	1		
DPDCH size / frame	10240		
Physical Channel rate (ksps)	1024		
FBI bits / slot	0		
Pilot bits / slot	6		
TFCH bits per slot	2		
TPC bits / slot	2		
DPCCH size / frame	160		

Second Method

[0035] In an alternative approach to the channel coding and rate matching required to multiplex several services, the arrangement shown in Figure 5 is used; in a small variation to Figure 4, the inputs at Step 1 in the BSC 18 are values of E_b/N_0 for each service and the number of bits in one time frame, $N_{b_{iti}}$; the current data rate is $R_B = N_{b_{iti}} \cdot 10$ ms.

[0036] $(E_b/N_0)_i$ indicates a QoS of service i which is handled by the BSC 18. After the channel coding step, which is specific to the service i and is described by the coding factor (coding gain) CF_i , when the number of coded bits $N_{codi} = N_{b_{iti}} \cdot CF_i$

[0037] This value is the input to a rate matching step, the output of which is $(E_s/N_0)_i$, the QoS after the coding and rate matching, and the number of symbols $N_{Si} = N_{codi} \cdot RF_i$

[0038] This second method depends on the assumption

$$\left(\frac{E_b}{N_0} \right)_i \cdot N_{b_{iti}} = \left(\frac{E_{cod}}{N_0} \right)_i \cdot N_{codi} = \left(\frac{E_s}{N_0} \right)_i \cdot N_{Si} \quad (4)$$

Eq. (4) may be rewritten using the coding factor CF_i and the rate matching factor RF_i (cf. eq. (5)). The number of repeated / punctured bits is simply given by $N_{RMI} = N_{Si} - N_{codi} = (RF_i - 1) \cdot N_{codi}$. Depending on the rate matching factor RF_i there are three possibilities:

- Repetition: $RF_i > 1$, i.e. $N_{Si} > N_{codi}$, $N_{RMI} > 0$
- Puncturing: $RF_i < 1$, i.e. $N_{Si} < N_{codi}$, $N_{RMI} < 0$
- No rate matching: $RF_i = 1$, i.e. $N_{Si} = N_{codi}$, $N_{RMI} = 0$

The linear approximation in eq. (4) is only valid if the puncturing does not exceed a certain ratio. Currently, in ETSI there is the working assumption, that puncturing should not exceed 20%, i.e. $RF_i \geq 0.8$! The rate matching factor RF_i is given by the product of the dynamic rate matching factor DRF and the semi static rate matching factor SFR_i by $RF_i = DRF \cdot SFR_i$. The dynamic rate matching factor DRF is equal for all multiplexed services, and the semi static rate matching factor SFR_i depends on the service. Two basic conditions must be fulfilled by the rate matching principle:

$$\left(\frac{E_s}{N_0} \right)_i = \left(\frac{E_{cod}}{N_0} \right)_i \cdot \frac{1}{RF_i} = \left(\frac{E_b}{N_0} \right)_i \cdot \frac{1}{DRF \cdot SFR_i \cdot CF_i} \approx const. \forall i = 1, \dots, n \quad (5)$$

$$\sum_{i=1}^n N_{Si} = \sum_{i=1}^n N_{codi} \cdot RF_i = DRF \cdot \sum_{i=1}^n N_{codi} \cdot SFR_i = N_S \quad (6)$$

The number of symbol bits in one time frame (10 ms) is derived by

$$N_S = 16 \cdot \sum_{i=1}^m N_{datai}$$

The value of $m > 1$ is used for multi-code transmission, i.e. more than one DPDCH is assigned to one CCTrCH. Single code transmission is described by $m = 1$. In the uplink the number of data bits N_{data} of one DPDCH in a time slot (0.625 ms) is simply given by $N_{data} = 10 \cdot 2^k$, $k = 0 \dots 6$. In the downlink, due to time multiplex of DPDCH and DPCCH it is given by $N_{data} = 20 \cdot 2^k \cdot N_{pilot} \cdot N_{TPC} \cdot N_{TFCL}$, $k = 0 \dots 6$. The spreading factor of the related DPCH in uplink and downlink is $SF = 256/2^k$, thus it may range from 256 down to 4.

[0039] With this approach and referring once more to Figure 4, after the slightly different inputs to Step 1, as explained above, Step 2 is different in that the rate matching factors are calculated as follows:-

Step 2: First, the following transformation is performed (cf. eq.4): $(E_{cod}/N_0)_i = (E_b/N_0)/CF_i$. Then a service $i=i_0$ with certain $(E_{cod}/N_0)_{i_0}$ requirement is chosen as reference, which has a semi static rate matching factor $SFR_{i_0} = 1$. From this all semi static rate matching factors for the remaining services can be derived by $SFR_i = (E_{cod}/N_0)_{i_0}/(E_{cod}/N_0)_i$, $i \neq i_0$. Such factors do not depend on the currently used data rates, they are a function of E_b/N_0 -requirement and the coding method. Thus, they are part of the semi-static part of the TFCL. Next, each service combination is taken into account. The spreading factor SF which is explicitly given by the number of symbol bits N_S must be chosen for each combination of data bits N_{biti} according to

$$\sum_{i=1}^n N_{datai} \cdot SFR_i = \sum_{i=1}^n N_{biti} \cdot CF_i \cdot SFR_i \leq N_S / DRF_{min} \quad (\text{cf. eq. (6), } DRF_{min} =$$

RF_{min}/SFR_{min} , $RF_{min} = 0.8$). Because N_S and hence SF depends on the currently used data rate, the spreading factor SF may be an element of the dynamic part of TFCL.

Step 3 is identical to that performed in the first method according to the invention.

Step 4 The dynamic rate matching factor is automatically given by

$$DRF = N_s / \left(\sum_{i=1}^n N_{i, \text{codi}} \cdot SRF_i \right) = N_s / \left(\sum_{i=1}^n N_{i, \text{biti}} \cdot CF_i \cdot SRF_i \right)$$

for a certain service combination. Note: N_{biti} is element of the dynamic part of TFCI (transport block set size), N_s is given by SF and CF_i comes from the used coding scheme. Now the rate matching factor for each service is calculated by $RF_i = DRF \cdot SRF_i$. From this, the number of punctured / repeated bits is simply $N_{\text{RMI}} = (RF_i - 1) \cdot N_{\text{codi}}$.

Step 5 is identical to the first method.

Example 2

[0040] In the following example of the second method according to the invention, a combination of 2 services assumed with the following parameters:-

- DCH₁: LCD data service with $E_B/N_0 = 5\text{ dB}$, 1/3 conv. coding + 8/9 Reed Solomon (e.g. video)
- DCH₂: UDD data service with $E_B/N_0 = 3\text{ dB}$, 1/3 conv. coding (e.g. packet data) The following three service combinations are permitted: {DCH₁, DCH₂} = {144/32, 64/64, 64/32} kBit/s. In table 3 Error! Reference source not found, the result for the semi static rate matching is shown. For illustration the values are given logarithmic in dB.

Table 3:

Determination of the semi static rate matching factor			
	DCH ₁ : LDD-service	DCH ₂ : UDD-service	Comments
E_B/N_0	5 dB	3 dB	
coding factor	5.2827 dB (27/8)	4.7712 dB (3/1)	$CF_{\text{dB}} = 10\log_{10}(CF)$
E_{cod}/N_0	-0.2827 dB	-1.7712 dB	$\Delta E_{\text{cod}}/N_0 = 1.4885\text{ dB}$
SRF_i	1.4088	1	$SRF = 10^{(\Delta E_{\text{cod}}/N_0)/10}$

In the current example, the service with the highest requirement on E_{cod}/N_0 was chosen for reference. It will be evident, that with the proposed rate matching algorithm at least this service needs no semi static rate matching. Table 4 shows the results for the dynamic part of the rate matching for the different assumed service combinations and the calculated number of bits.

Table 4:

Dynamic Rate Matching for different Service Combinations			
	DCH ₁ : LDD-service	DCH ₂ : UDD-service	Comments
144/32 N_{biti}	1440	336 (16 bit MAC)	TB set size
N_{codi}	4860	1008	$N_s = 10240$, SF = 4 DRF = 1.3037
$N_{\text{sixteenths}}$	8926	1314	
E_S/N_0	-2.9230	-2.9230	$\Delta E_S/N_0 = 0.222\text{ dB}$
E_S/N_0 w/o RM	-2.7008	-4.1893	
64/64 N_{biti}	640	772 (32 bit MAC)	TB set size
N_{codi}	2160	2016	$N_s = 5120$, SF = 8 DRF = 1.0121
$N_{\text{sixteenths}}$	3080	2040	
E_S/N_0	-1.8234	-1.8234	$\Delta E_S/N_0 = 0.6556\text{ dB}$
E_S/N_0 w/o RM	-1.1678	-2.6563	
64/32 N_{biti}	640	336 (16 bit MAC)	TB set size

Table 4: (continued)

Dynamic Rate Matching for different Service Combinations			
	DCH ₁ : LDD-service	DCH ₂ : UDD-service	Comments
N_{codi}	2160	1008	$N_S=5120$, SF=8 DRF = 1.2639
$N_{\text{sixteenths}}$	3846	1274	
E_S/N_0	-2.7883	-2.7883	$\Delta E_S/N_0 = 0.4208$ dB
E_S/N_0 w/o RM	-2.3675	-3.8560	

[0041] The number of data bits for the LDD service is simply given by its data rate i.e. $N_{\text{bitLDD}} = R_{\text{bitLDD}} \cdot 10\text{ms}$. For the UDD service an additional MAC header for e.g. addressing purposes of 16 bits is assumed, i.e. $N_{\text{bitUDD}} = R_{\text{bitUDD}} \cdot 10\text{ms} + 16$ bit. In the example, this bit numbers are equal to the transport block set size. Because the uplink is considered, the number of available symbol bits is simply given by $N_S = 40960/\text{SF}$. The value of $\Delta E_S/N_0$ describes the improvement in E_S/N_0 by use of the proposed rate matching method compared to missing it. The description of the specified service combinations is as follows:

- LDD144/UDD32: The sum of all coded data bits including semi static rate matching is

$$\sum_{i=1}^n N_{\text{codi}} \cdot \text{SRF}_i = 7855,$$

DRF_{min} = 0.8 (SFR_{min} = 1). The next lowest symbol rate would be $N_S = 5120$, i.e. SF = 8. According to eq. 6 a DRF < 0.8 would be necessary. Thus, the next highest SF = 4 is chosen with $N_S = 10240$. The other results can be found in table 4. Using this constellation an improvement in E_S/N_0 of $\Delta E_S/N_0 = 0.222$ dB can be achieved. Since the transmission power is directly related to E_S/N_0 this leads to a decrease of the transmission power of 0.222 dB, too.

- LDD64/UDD64: Here,

$$\sum_{i=1}^n N_{\text{codi}} \cdot \text{SRF}_i = 5059.$$

Thus, SF = 8 is chosen with $N_S = 5120$. For this service combination, an improvement of $\Delta E_S/N_0 = 0.6556$ dB can be achieved.

- LDD64/UDD32: For the last examined service combination

$$\sum_{i=1}^n N_{\text{codi}} \cdot \text{SRF}_i = 4051.$$

As in the previous case SF = 8 is chosen with $N_S = 5120$. Now the improvement is $\Delta E_S/N_0 = 0.4208$ dB.

[0042] The second example has many of the advantages of the first method according to the invention.

Claims

1. In a UMTS network in which a plurality of services of a single user having different transmission power requirements are multiplexed in one channel and the technique of rate matching is applied, a method of determining for each service the number of bits to be punctured or repeated characterised by the steps of:-

deriving for each service the Energy per Bit per Noise density E_B/N_0 required to achieve a desired Bit Error Rate;

for each E_B/N_O deriving a value of the Energy per coded Symbol per Noise density E_S/N_O ;

and from the E_S/N_O deriving a rate matching factor by which that E_S/N_O can be matched to the minimum Energy per coded Symbol per Noise density applicable to said one channel.

2. A method according to Claim 1 comprising the initial step of generating for each service a look up table containing the value of E_B/N_O required for each spreading factor used and for every environment likely to be encountered.
3. A method according to Claim 2 in which the look up table is stored in the physical layer of the UMTS.
4. A method according to any preceding claim further comprising deriving the semi static rate matching factor and the spreading factor for each service.
5. A method according to Claim 4 comprising performing the derivations of semi static rate matching factor and spreading factor in the Radio Resource Control of the UMTS; transmitting the values to the physical layer of the UMTS; and in the physical layer performing puncturing or repetition in accordance with the transmitted values and the values in the look up table.
6. A method according to Claim 4 or Claim 5 in which the rate matching factor is derived by generating a semi static rate matching factor for each service and multiplying the semi static rate matching factor by a dynamic rate matching factor which is equal for all services to be multiplexed.
7. A method according to Claim 6 in which the semi static rate matching factor is normalised by division by the coding gain associated with said factor which gain is limited to greater than - 1 dB.
8. A method according to Claim 7 in which the semi static rate matching factor and the spreading factor for each service are derived by estimating an initial spreading factor dependent on the number of bits per frame being greater than the sum of the data rates for all services to be multiplexed; comparing the initial spreading factor with said look up table of values of E_S/N_O for each service and for all likely environments and levels of coding to determine the appropriate set of E_S/N_O .
9. A method according to Claim 4 or Claim 5 in which the rate matching factor is derived by setting the E_S/N_O of the Coded Composite Transport Channel equal to the E_S/N_O of a service times the inverse of the rate matching factor.
10. A method according to Claim 4 or Claim 5 in which the rate matching factor is derived by setting the E_S/N_O of a service equal to the Quality of Service after channel coding of that service times the inverse of the rate matching factor.
11. A UMTS comprising a UMTS core network; a plurality of Base Station Controllers; associated with each BSC a plurality of Base Transmission Systems; and associatable with each BTS a plurality of mobiles, characterised by every mobile comprising storage means to store a look up table of the number of bits for rate matching required for each service and environment likely to be encountered for each value of E_B/N_O ; and each BSC comprising means to transmit to each mobile and to each BTS values of spreading factor and semi static rate matching factor for a combination of services to be multiplexed in one channel to or from that mobile.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 99 30 5516

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
A	US 5 581 575 A (ZEHAVI EPHRAIM ET AL) 3 December 1996 (1996-12-03) * abstract * * column 4, line 26 - line 67 * * column 5, line 21 - column 6, line 58 * * column 8, line 22 - line 39 * * column 9, line 23 - column 10, line 21 * * claim 1 *	1-11	H04Q7/38 H04L1/00 H04L1/08
A	US 5 309 474 A (GILHOUSEN KLEIN S ET AL) 3 May 1994 (1994-05-03) * column 22, line 25 - line 65 *	1-11	
A	EP 0 627 827 A (CSELT CENTRO STUDI LAB TELECOM ; PHILIPS ELECTRONICS NV (NL)) 7 December 1994 (1994-12-07) * abstract * * page 2, line 1 - line 10 * * page 2, line 48 - page 4, line 10 * * claim 7 *	1-11	
A	US 5 822 318 A (GILHOUSEN KLEIN S ET AL) 13 October 1998 (1998-10-13) * abstract * * column 2, line 66 - column 3, line 34 * * column 5, line 35 - column 6, line 10 * * column 8, line 22 - line 36 * * column 12, line 10 - line 24 *	1-11	TECHNICAL FIELDS SEARCHED (Int.Cl.7) H04L
A	BERRUTO E ET AL: "VARIABLE-RATE FOR THE BASIC SPEECH SERVICE IN UMTS" PROCEEDINGS OF THE VEHICULAR TECHNOLOGY CONFERENCE, US, NEW YORK, IEEE, vol. CONF. 43, 1993, page 520-523 XP000393235 ISBN: 0-7803-1267-8 * page 520 - page 522, Section I - Section III *	1-11	
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 23 December 1999	Examiner Koukourlis, S
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

EPO FORM 1503 02/92 (P04001)



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 99 30 5516

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
A	FRENGER P ET AL: "RATE MATCHING IN MULTICHANNEL SYSTEMS USING RCPC-CODES" IEEE VEHICULAR TECHNOLOGY CONFERENCE, US, NEW YORK, IEEE, vol. CONF. 47, page 354-357 XP000701819 ISBN: 0-7803-3660-7 * page 354 * * page 357, Section V - Section VI *	1,5	
A	US 5 909 434 A (ZEHAVI EPHRAIM ET AL) 1 June 1999 (1999-06-01) * abstract * * column 5, line 37 - line 58 * * column 6, line 1 - line 18 * * figure 2 *	1,5	
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 23 December 1999	Examiner Koukourlis, S
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EPO FORM 1500 (03.02) (P04001)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 30 5516

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

23-12-1999

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 5581575 A	03-12-1996	AU 702655 B	25-02-1999
		AU 8094394 A	23-05-1995
		BR 9407918 A	26-11-1996
		CA 2174343 A	11-05-1995
		CN 1133661 A	16-10-1996
		EP 0727120 A	21-08-1996
		FI 961825 A	28-06-1996
		IL 111452 A	06-12-1998
		JP 9507119 T	15-07-1997
		WO 9512943 A	11-05-1995
		ZA 9408427 A	30-06-1995
US 5309474 A	03-05-1994	US 5103459 A	07-04-1992
		US 5715236 A	03-02-1998
		AU 652956 B	15-09-1994
		AU 8401691 A	23-01-1992
		BG 61514 B	31-10-1997
		BG 97222 A	27-05-1994
		CA 2085890 A	26-12-1991
		CN 1061312 A	20-05-1992
		CZ 283123 B	14-01-1998
		EP 0536334 A	14-04-1993
		FI 925812 A	21-12-1992
		HU 216989 B	28-10-1999
		HU 64657 A	28-01-1994
		IL 98598 A	27-02-1994
		JP 2958433 B	06-10-1999
		JP 6501349 T	10-02-1994
		KR 134390 B	27-04-1998
		MX 173818 B	29-03-1994
		NO 925019 A	23-12-1992
		PT 98079 A, B	31-08-1993
		SG 52735 A	28-09-1998
		SK 387192 A	10-08-1994
		WO 9200639 A	09-01-1992
		US 5511073 A	23-04-1996
		US 5504773 A	02-04-1996
		US 5659569 A	19-08-1997
		US 5535239 A	09-07-1996
		US 5629955 A	13-05-1997
		US 5568483 A	22-10-1996
		US 5841806 A	24-11-1998
		US 5943361 A	24-08-1999
		US 5416797 A	16-05-1995
EP 0627827 A	07-12-1994	IT 1270938 B	16-05-1997

EPO FORM P055

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 30 5516

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

23-12-1999

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 0627827 A		FI 942253 A	15-11-1994
		JP 2641030 B	13-08-1997
		JP 7143572 A	02-06-1995
		US 5490136 A	06-02-1996
US 5822318 A	13-10-1998	AU 687227 B	19-02-1998
		AU 3093695 A	04-03-1996
		BR 9506276 A	12-08-1997
		CA 2169649 A	15-02-1996
		CN 1130963 A	11-09-1996
		EP 0721704 A	17-07-1996
		FI 961414 A	20-05-1996
		JP 9506231 T	17-06-1997
		WO 9604718 A	15-02-1996
		ZA 9505940 A	01-02-1996
US 5909434 A	01-06-1999	AU 3291597 A	05-01-1998
		EP 0903023 A	24-03-1999
		WO 9745976 A	04-12-1997

EPO FORM P0429

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82